

# FLOS

F4550009 White

## Nebula

Designed by Joris Laarman, 2007




Halogen - 12 x 840W

Suspension luminaire providing diffused lighting. Central body in die-cast aluminum and 10 blown glass cones of different sizes. Bayonet-type coupling system of the cones for easy cleaning. Die-cast aluminum ceiling attachment with spherical automatic wire clamp. Polycarbonate rose.

Are you a professional and your project needs consulting and support?

[BOOK AN APPOINTMENT](#)



### Main specifications

EAN	8059607020081
Mounting	Suspension
Environment	Indoor dry location
Light source type	Bulb
Lamp category	Halogen
Lamp holder	E27
Ilcos	HSGSA/S + HSGS
Number of heads	12
Power (W)	840

### Physical

Colour	White
Cord length (mm)	5000
Net weight (kg)	41.5
Package height (cm)	185
Package width (cm)	122
Package length (cm)	82
Package volume (m <sup>3</sup> )	1.84
IP	20
IP external	20

### Download

[Mounting instructions](#)  PDF

[Spare Parts](#)  PDF

### Photometric Files


[LDT / IES](#)  LDT

### Technical Drawings

[2D](#)  ZIP



## Schematic light drawing



Luminous flux luminaire  
12800 lm

The above drawing is for illustrative purposes only and refers to product code: F4550009WNEBULA\_12X70W-HL

### Photometric

Lighting type	Total
Light distribution	Asymmetric

### Electrical

Insulation class	I
Frequency (Hz)	50/60
Main voltage (Vac)	220-250
Cord length (mm)	5000
Batteries inside	No
Charging min time	No


## Bulbs



NOT INCLUDED

RF4551000


Kit LED Nebula Lamps 12x8W E27  
220-240V 2700K



NOT INCLUDED

RF32563

LED Lamp 11.5W E27 220-240V  
2700K A70



NOT INCLUDED

RF32770

LED Lamp 7W lm E27 220-240V  
2700K A60



NOT INCLUDED

RF32564

LED Lamp 11.5W E27 220-240V  
3000K A70

## Spare Parts



RF04487

Porcelain E27 lamp holder



RF4550100

Diffuser "B" assembly spare part



RF4550200

Diffuser "D" assembly spare part



RF4550300

Diffuser "I" assembly spare part



RF4550400

Diffuser "H" assembly spare part



RF4550500

Diffuser "E" assembly spare part



RF4550600

Diffuser "G" assembly spare part



RF4550700

Diffuser "C" assembly spare part



RF4550800

Diffuser "F" assembly spare part